



**Diesel Generator
Sales, Installation,
Hire, Spares, Service
& Refurbishment**



Certificate No: 1152

Model YH6.8PTRL - 6.8kVA Honda Petrol Generator

GENERAL	
OUTPUT RATINGS	
50Hz, 230 VOLT, SINGLE PHASE	
Prime Rating	6.8kVA 5.5kW 1500 RPM
ENGINE MAKE	Honda
ENGINE MODEL	GX 390



TECHNICAL DATA			
Engine Model	GX 390	Protection Class	IP23
Start	Recoil	Insulation Class	H
Frequency	50Hz	Fuel Cons: (l/hr)	2.5
Volts	230	Sound Attenuation	84 DbA @ 1M
Oil Capacity	1.1 Litres	Alternator Type	Without collar or brush
Fuel Tank Capacity	6.1 Litres	Regulation	Mechanical

Rating Definitions

Prime power: No limitation to annual hours of operation and these models can supply 10% overload for 1 in 12 hours.

Standby power: Ratings only applicable for supplying power in event of power failure. No overload is permitted on these ratings.

DIMENSIONS AND WEIGHTS				
Length Cm	Width Cm	Height Cm	Dry Weight Kg	Fuel Consumption L/hr
71.5	57	59	76	2.5



Registered Office:
Yorpower Limited
Electricity Building
Blenheim Road
Pocklington Industrial Estate
York, YO42 1NR
UNITED KINGDOM



T: +44 (0) 1759 305400
F: +44 (0) 1759 305405
E: sales@yorpower.com
W: www.yorpower.com