

Total Control At The Touch Of A Button

POWERWIZARD 1.0

FG Wilson's new range of digital control panels gives you the industry leading control solution for all your power needs.

The PowerWizard 1.0 control system offers a cost effective way of monitoring and communicating with your generating set. Using cutting edge technology, meters, gauges and dials are integrated into one display, giving you quick and easy access to controls, metering, protection device settings and diagnostic information.


Why should you choose an FG Wilson PowerWizard 1.0 series control panel?

- Common look and feel from 10 to 2000 kVA for ease of operation and service
- 9-32V DC providing a single module to cover whole product range
- Simple menu layout for ease of navigation and monitoring
- Two display languages, (English and a customer language*) to aid service and commissioning
- Last 20 event log to aid fault finding
- Robust electronic package for industry leading reliability
- Configurable using front key pad/laptop
- Shortcut keys for immediate access to engine or AC metering
- Integrated metering and controls reducing components and wiring aiding reliability and ease of service
- Common engine wiring system allows simple upgrading between levels of panel
- Can be serviced used standard EST tool

* See languages available overleaf



Typical view of panel display after pressing the 'Engine' shortcut key



Typical view of panel display after pressing the 'AC' shortcut key

*See languages available overleaf



STANDARD FEATURES

- **PANEL CONSTRUCTION AND FINISH**
Components installed in a heavy duty sheet steel
Phosphate chemical pre-coating of steel provides corrosion resistant surface
Polyester composite powder topcoat forms high gloss and extremely durable finish
Lockable-hinged panel door provides for easy component access
- **MOUNTING**
Mounted to generating set baseframe on robust steel stand
Vibration isolated from generating set

• INSTRUMENTATION

LCD Display with adjustable contrast and backlight with auto power off

AC Metering:

Volts 3-phase (L-L & L-N)
Amps (per phase & average)
Frequency

DC Metering:

Battery Volts
Engine Hours Run
Engine Jacket Water Temperature (in °C or °F)
Lube Oil Pressure (in psi, kPa or bar)
Engine Speed (RPM)

• PROTECTION

Fail to start
Low Oil Pressure
High Engine Temperature
Low / High Battery Voltage
Battery Charger Failure (if fitted)
Under-speed, Over-speed
Loss of Engine Speed Detection
2 spare fault channels
20 Event fault log (name of event, engine hours at first occurrence of event, engine hours at latest occurrence of event, number of occurrences of event)

• CONTROLS

2 LED status indication (1 red shutdown, 1 amber warning)
Run key & LED indicator
Auto key & LED indicator
Stop key & LED indicator
Lamp Test key
Alarm Acknowledgement key
Menu navigation keys
Engine and AC metering shortcut keys
All control module keys have tactile feedback
Lock down emergency stop push button
CAN 1 data link - J1939 for communicating with electronic engine control modules

• LANGUAGES

LED Displays available in Arabic, Chinese, Danish, Dutch, Finnish, French, German, Greek, Hungarian, Icelandic, Italian, Norwegian, Portuguese, Russian, Spanish and Swedish

OPTIONAL FEATURES

• BATTERY CHARGER

Battery trickle charge ammeter
Engine coolant heater controls
Volt free contacts for:
Common Alarm
Genset running

• AUDIBLE ALARM

Lockdown emergency stop button with security key
Volts adjust potentiometer
Speed adjust potentiometer

• SPARE SHUTDOWN/ALARM CHANNEL CAN INCLUDE:

Earth leakage protection
Low fuel level
Low coolant level
High lube oil temperature
Low coolant temperature
High fuel level
Overload via alarm switch
Earth fault protection

Note: All options are not available on all genset models

Tel: +44 (0) 1924 455350
Fax: +44 (0) 1924 451001
sales@progress-group.com
www.progress-group.com



Authorised Service Dealer

Progress Group
Dale Works, Brewery Lane
Thornhill Lees
Dewsbury
West Yorkshire
WF12 9HU


Progress Group
Supplying Power Worldwide