



**YORPOWER**

RATING	MODEL	ENGINE
148kVA Open Set	YXP148D6	Perkins®

GENERAL	
<b>OUTPUT RATINGS 60Hz,</b>	
<b>Prime</b>	<b>148kVA, 118kW</b>
<b>Standby</b>	<b>163kVA, 130kW</b>
<b>ENGINE</b>	<b>PERKINS 1006TAG</b>
<b>ALTERNATOR</b>	<b>LEROY SOMER</b>



TECHNICAL DATA			
Engine Model	1006TAG	Engine Speed	1800RPM
Cylinders	6	Fuel Cons: 100% Load (l/hr)	37.6
Displacement	5.99 Litres	Fuel Cons: 75% Load (l/hr)	28.9
Coolant Capacity	37.2 Litres	Oil Capacity	19 Litres
Cooling	Water Cooled	DBA @ 7M	TBC
Fuel Tank Capacity	420	Intake System	Turbocharged

These ratings are suitable for Prime Continuous power output at varying load with no limitation on annual hours of operation.  
The Generator will supply 10% overload for 1 in 12 hours.

GENERAL ARRANGEMENT	

DIMENSIONS AND WEIGHTS			
Length mm	Width mm	Height Mm	Weight Kg
TBC	TBC	TBC	TBC

We reserve the right to amend specifications without notice. All ratings are at standard ISO conditions  
Alternators may vary subject to lead time and availability

Registered Office:  
Yorpower Limited  
Unit 2, Hurricane Close  
Sherburn In Elmet  
LS25 6PB  
UNITED KINGDOM



**T: +44 (0) 1977 688155**  
**F: +44 (0) 1977 688158**  
E: sales@yorpower.com  
W: www.yorpower.com

Yorpower Limited, Registered in England and Wales No. 7035780